



Test Report No.: FM2009WDG0427



RF EXPOSURE REPORT

Applicant	Particle Industries, Inc
Address	126 Post St,4th floor, San Francisco, CA 94108 USA

Manufacturer or Supplier	Particle Industries, Inc
Address	126 Post St,4th floor, San Francisco, CA 94108 USA
Product	Tracker One LTE M1
Brand Name	Particle
Model	ONE402M
Additional Models & Model Difference	ONE404M, ONE402M-NB, ONE404M-NB
Date of tests	Aug. 18, 2020 ~ Sep. 10, 2020

- FCC Part 2 (Section 2.1091)
- KDB 447498 D01
- IEEE C95.1

CONCLUSION: The submitted sample was found to COMPLY with the test requirement

Tested by Breeze Jiang Senior Project Engineer / EMC Department	Approved by Glyn He Assistant Manager / EMC Department
	
	Date: Dec. 21, 2020

This report is governed by, and incorporates by reference, CPS Conditions of Service as posted at the date of issuance of this report at <http://www.bureauveritas.com/home/about-us/our-business/cps/about-us/terms-conditions/> and is intended for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. Measurement uncertainty is only provided upon request for accredited tests. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence or if you require measurement uncertainty; provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents.

Bureau Veritas Shenzhen Co., Ltd.
Dongguan Branch

No. 96, Guantai Road (Houjie Section), Houjie
Town, Dongguan City, Guangdong Province.
523942. People's Republic of China.

Tel: +86 769 8998 2098
Fax: +86 769 8593 1080
Email: customerservice.dg@cn.bureauveritas.com



Test Report No.: FM2009WDG0427

TABLE OF CONTENTS

RELEASE CONTROL RECORD	3
1. CERTIFICATION.....	4
2. RF EXPOSURE LIMIT	5
3. MPE CALCULATION FORMULA.....	5
4. CLASSIFICATION	5
5. ANTENNA GAIN	6
6. CALCULATION RESULT OF MAXIMUM CONDUCTED POWER.....	6



Test Report No.: FM2009WDG0427

RELEASE CONTROL RECORD

ISSUE NO.	REASON FOR CHANGE	DATE ISSUED
FM2009WDG0427	Original release	Dec. 21, 2020

Bureau Veritas Shenzhen Co., Ltd.
Dongguan Branch

No. 96, Guantai Road (Houjie Section), Houjie
Town, Dongguan City, Guangdong Province.
523942. People's Republic of China.

Tel: +86 769 8998 2098
Fax: +86 769 8593 1080
Email: customerservice.dg@cn.bureauveritas.com

1. CERTIFICATION

FCC ID:	2AEMI-ONE40X
PRODUCT:	Tracker One LTE M1
BRAND NAME:	Particle
MODEL NO.:	ONE402M
ADDITIONAL MODELS:	ONE404M, ONE402M-NB, ONE404M-NB
TEST SAMPLE:	Engineering Sample
APPLICANT:	Particle Industries, Inc
STANDARDS:	FCC Part 2 (Section 2.1091)
	KDB 447498 D01
	IEEE C95.1

Note: Additional models ONE404M, ONE402M-NB, ONE404M-NB are identical with the test model ONE402M except the model number for marketing purpose.

2. RF EXPOSURE LIMIT

LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

FREQUENCY RANGE (MHz)	ELECTRIC FIELD STRENGTH (V/m)	MAGNETIC FIELD STRENGTH (A/m)	POWER DENSITY (mW/cm ²)	AVERAGE TIME (minutes)
LIMITS FOR GENERAL POPULATION / UNCONTROLLED EXPOSURE				
300-1500	F/1500	30
1500-100,000	1.0	30

F = Frequency in MHz

3. MPE CALCULATION FORMULA

$$Pd = (Pout * G) / (4 * pi * r^2)$$

where

Pd = power density in mW/cm²

Pout = output power to antenna in mW

G = gain of antenna in linear scale

Pi = 3.1416

R = distance between observation point and center of the radiator in cm

4. CLASSIFICATION

The antenna of this product, under normal use condition, is at least 20cm away from the body of the user. So, this device is classified as **Mobile Device**.



5. ANTENNA GAIN

The antennas provided to the EUT, please refer to the following table:

Transmitter Circuit	Peak Gain (dBi)	Antenna Type
BT-LE	1.71	FPCB Antenna
	0	Ceramic Antenna
WIFI	1.71	FPCB Antenna

6. CALCULATION RESULT OF MAXIMUM CONDUCTED POWER

The tuned conducted Average Power (declared by client)

Mode	Frequency (MHz)	Target Power (dBm)	Tolerance (dBm)	Lower Tolerance (dBm)	Upper Tolerance (dBm)
BT-LE (GFSK)	2402-2480MHz	8	+1	7	9
802.11b	2412-2462MHz	16	+1	15	17
802.11g	2412-2462MHz	16	+1	15	17
802.11n HT20	2412-2462MHz	16	+1	15	17
802.11n HT40	2422-2452MHz	16	+1	15	17

The measured conducted Average Power

Mode	Frequency (MHz)	Averaged Power (dBm)
BT-LE (GFSK)	2440	7.81
802.11b	2462	16.60
802.11g	2462	15.97
802.11n HT20	2462	15.99
802.11n HT40	2422	15.93

FREQUENCY BAND(MHz)	MAX AVERAGE POWER(dBm)	ANTENNA GAIN(dBi)	DISTANCE (cm)	POWER DENSITY (mW/cm ²)	LIMIT (mW/cm ²)
BT 2402-2480	9	1.71	20	0.002343	1.0
WiFi 2412-2462	17	1.71	20	0.014782	1.0

CONCLUSION:

The BT and WLAN can transmit simultaneously, the formula of calculated the MPE is:

$$CPD1 / LPD1 + CPD2 / LPD2 + \dots \text{etc.} < 1$$

CPD = Calculation power density

LPD = Limit of power density

$$(0.002343/1)+(0.014782/1) = 0.017125 < 1, \text{ which is less than the "1" limit.}$$

--- END ---